

Таблица расчета сечения питающих кабелей

Общее потребление тока, А	Длина кабеля	4-7ft/ 1,2-2,1м		7-10ft/ 2,1-3м		10-13ft/ 3-3,9м		13-16ft/ 3,9-4,8м		16-19ft/ 4,8-5,7м		19-22ft/ 5,7-6,6м		22-28ft/ 6,6-8,4м	
		AWG	mm ²	AWG	mm ²	AWG	mm ²	AWG	mm ²	AWG	mm ²	AWG	mm ²	AWG	mm ²
0-20		12	4,0	12	4,0	10	6,0	10	6,0	8	8,0	8	8,0	8	8,0
20-35		10	6,0	8	8,0	8	8,0	6	15,0	6	15,0	6	15,0	4	20,0
35-50		8	8,0	8	8,0	6	15,0	4	20,0	4	20,0	4	20,0	4	20,0
50-65		8	8,0	6	15,0	4	20,0	4	20,0	4	20,0	4	20,0	2	35,0
65-85		6	15,0	4	20,0	4	20,0	2	35,0	2	35,0	2	35,0	0	50,0
85-105		6	15,0	4	20,0	2	35,0	2	35,0	2	35,0	2	35,0	0	50,0
105-125		4	20,0	4	20,0	2	35,0	0	50,0	0	50,0	0	50,0	0	50,0
125-150		2	35,0	2	35,0	0	50,0	0	50,0	0	50,0	0	50,0	0	50,0